




Nokia Manual Setup

WAP Settings

- 1 Main Menu › Settings › Configuration › Personal configuration settings › Add › Web
- 2 Enter the details for the following parameters

Account Name	Vodafone wap 	2degrees wap 	Telecom wap 
User Name	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>
Password	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>
Use Preferred access point	No	No	No

- 3 Select 'Access point Settings'

Proxy	Enable	Enable	Enable
Proxy address	172.030.038.003	118.148.1.118	210.55.11.73
Proxy Port	8080	8080	80
Data bearer	Packet Data	Packet Data	Packet Data




- 4 Select 'Bearer Settings'

Packet data acc. Pt.	live.vodafone.com	2degrees	wap.telecom.co.nz
Network type	IPv4	IPv4	IPv4
Authentication type	Normal	Normal	Normal
User Name	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>
Password	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>

- 5 Go back to Personal accounts
- 6 Push 'options', then activate

MMS Settings

- 1 Main Menu › Settings › Configuration › Personal configuration settings › Options › Add New › Multimedia msg
- 2 Enter the details for the following parameters

Account Name	Vodafone mms 	2degrees mms 	Telecom mms 
Server address	http://pxt.vodafone.net.nz/pxtsend	http://mms.2degreesmobile.net.nz:48090	http://lsmmsc.xtra.co.nz
Use pref. access pt.	No	No	No

- 3 Select 'Access point settings'

Proxy	Enable	Enable	Enable
Proxy address	172.030.038.003	118.148.1.118	210.55.11.73
Proxy Port	8080	8080	80

- 4 Select 'Bearer Settings'

Packet data acc. Pt.	live.vodafone.com	mms	wap.telecom.co.nz
Network type	IPv4	IPv4	IPv4
Authentication type	Normal	Normal	Normal
User Name	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>
Password	<i>Leave Blank</i>	<i>Leave Blank</i>	<i>Leave Blank</i>

- 5 Go back to Personal accounts
- 6 Push 'options', then activate

Note: you need to send a photo before you can receive one